



### LED COMPAR RGBWA

CH1	Master Dimmer	000-255 0-100%
CH2	Strobe	000-007 No Function 008-255 Strobe slow to fast
CH3	Red	000-255 0-100%
CH4	Green	000-255 0-100%
CH5	Blue	000-255 0-100%
CH6	White	000-255 0-100%
CH7	Amber	000-255 0-100%
CH8	Effect	000 - 004 Blackout 005 - 080 Colour Macro (Colour 1 ~ Colour 31) 081 - 150 Colour Jumping (slow to fast) 151 - 220 Colour Fading (slow to fast) 221 - 255 Sound Control (microphone sensitivity).

### LED RGBW 5ch par64

CH1	MASTERDIMMER
CH2	RED
CH3	GREEN
CH4	BLUE
CH5	WHITE

## Lichtplan Cultuurhuus Braakhekke

Tel. 0570-542420 email.  
info@cultuurhuusbraakhekke.nl

Techniek, Bert Krukkeland: bert@kabaal.com

1kW PC

1kW Fresnel

Profiel 23-50

1kW Par CP62

Ledpar

Extra aanwezig:  
4x 0,5kW profiel 25  
2x 0,5kW profiel 20-40  
4x 0,5kW PC  
DMX splitter

Trekken vast, licht met  
ladder inhangen.

DMX Zaallicht 510-511-512

Regietafels: Strand200 plus 24/48  
AVOlites Titan Mobile

versie: 2020